

Call Routing Examples

Ignore Display Updates

Condition

Description: Rank: 10

Matching: All Stop Policy: Continue

Condition: Standard Information Name: Destination Address Expression: (.*)

Condition: (Please Select One)

Condition: (Please Select One)

Condition: (Please Select One)

Condition: (Please Select One)

Actions to perform if condition matches

Action: Export Variable Name: ignore_display_updates Value: true

Action: Bridge to Trunk Trunk: to_ITSP Destination: \$1

Action: (Please Select One)

Action: (Please Select One)

Action: (Please Select One)

Actions to perform if condition doesn't match

Action: (Please Select One)

Action: (Please Select One)

Use P-Asserted-Identity

Condition

Description: Rank: 10

Matching: All Stop Policy: Continue

Condition: Standard Information Name: Destination Address Expression: (.*)

Condition: (Please Select One)

Condition: (Please Select One)

Condition: (Please Select One)

Condition: (Please Select One)

Actions to perform if condition matches

Action: Set Variable Name: sip_h_Privacy Value: id

Action: Bridge to Trunk Trunk: to_ITSP Destination: \$1

Action: (Please Select One)

Action: (Please Select One)

Action: (Please Select One)

Actions to perform if condition doesn't match

Action: (Please Select One)

Action: (Please Select One)

Action: (Please Select One)

Action: (Please Select One)

Action: (Please Select One)

Save Cancel

Use P-Preferred-Identify

Condition (Please Select One)					
Actions to perform if condition matches					
Action	Export Variable	Name	forward_talk_and_hold_notifications	Value	true
Action	Export Variable	Name	enable-100rel	Value	true
Action	Export Variable	Name	sip_cid_type	Value	pid
Action	Export Variable	Name	origination_privacy	Value	hide_name
Action	Bridge to Trunk	Trunk	ITSP	Destination	S1

Rate Limit Inbound calls from any calling party, per calling party

useful to prevent malicious dialers from repeated call attempts

The below screenshot is rate limiting a specific source for more than 1 call attempt with 8 seconds.

(alter as needed)

If the rate limit is reached/triggered, a 404 response will occur

Basic Call Routing - To_ITSP

Description: **to_PBX**
Trace Call: **Disable**
Default Response: **404**

[Edit](#) [Cancel](#)

Rule

Showing 1 to 1 of 1 entries

#	Description	
10	IF MATCH Condition(All,Standard Information[Destination Address] = (.*)) THEN Custom[limit]=hash \${sip_network_ip} \${sip_from_user} 1/8"> Bridge to Trunk[to_PBX]=\$1 AND Continue	Edit Delete

[Add](#)